



## Granville Pin And Bush Grease

400g Cart & 12.5kg

### Product Description

Pin & Bush Grease is a tenacious grease designed for heavy duty applications where adhesion, shock loading and good corrosion protection is needed. It has proven to be ideal for use on bucket pins and bushes on heavy earth moving equipment, crane slews and also as an assembly and running in compound. The presence of graphite will fill surfaces and distribute load evenly preventing further wear and is therefore particularly suitable to extend the life of worn components.

### Product Benefits

- \* A high level of lubricating solids keep working surfaces apart and substantially extends component life
- \* Being fully resistant to the wet, extends the life of the lubricant and protects components from corrosion
- \* Adhesion improves provide increased lasting protection



\* Image for illustrative purposes only.

Size	Part No	Barcode
400g Cart	2760	5020618027607
12.5kg	2761	5020618027614

### Product Usage

Pin & Bush Grease can be applied by hand or by using a standard grease gun. Due to the high lubricating solids content, Pin & Bush Grease is not recommended for use on anti-friction bearings.

### Storage Instructions

Store sealed in a cool dry place

### Shelf Life

3 years from date of manufacture.

### Specification Information

Operating temperature range: -20°C to +140°C

Melting Point: 175°C

NLGI classification: 2/3

Worked Penetration: 250 to 295

- Appearance** : Grey/black smooth adhesive grease.
- Odour** : Characteristic
- Solubility** : Insoluble in water
- Kinematic Viscosity @ 40°C** : Base Oil - 180 cSt





## Granville Pin And Bush Grease

400g Cart & 12.5kg

### Safety Precautions

Please see our latest EC Safety Data Sheets for details.

### Transport Classification

Please see our latest EC Safety Data Sheets for details.

*\* The information contained in this leaflet is provided to enable the user to assess the product and should not be taken as a specification. All information provided is given in good faith, we can however not assume liability. It is up to the user to ensure that the information and the product is suitable for the use intended.*

Revision: 1 | Date: 04/05/2012

